

Component List and Illustrations

Section 6

INTERCONNECTIONS

Ref	Value	Description	Tol %±	Part No.	Ref	Value	Description	Tol %±	Part No.
RESISTORS					CAPACITORS (Contd.)				
R1	22k	CP		A4/35986	C40	.1μF	PE	400V	29495
R2	22k	CP		A4/35986	C45	.01μF	CE(2)	500V	24902
R3	470	CP	With S13	A4/36070	C51	47000μF	E	10V	36024
R4	470	CP	With S14	A4/36070	C90	5600pF	CE(2)	500V	22394
R5					C91	4.7μF	E	63V	32195
R6	5k	CP	Part of S6		C92	.047μF	CE(2)	30V	2793
R7	22k	CP	With S7	A4/35338	C93	1μF	CE(2)	1 63V	24888
R8	1k + 1k	CP	R8a + R8b	A4/36069	C94	.01μF	PE	1 160V	24886
R22	22	CF		28710	C95	6/25pF	TRIMMER		23593
R23	22	CF		28710	C96	47pF	CE(2)		685
R24	990k	MF	½	31927	RECTIFIERS				
R25	22	CF		28710	BR51	WO4			29367
R26	470k	CC	¼W	4906	BR52	WO4			29367
R27	1M	MF		26346	BR53	WO4			29367
R28	18	CF		28709	BR54	WO4			29367
R29	16k	MF		29361	BR55	VH148			36281
R30	15k8	MF		33291	SWITCHES				
R31	5k23	MF		33290	S1				A3/31292
R32	1k72	MF		33289	S2				A3/31292
R33	787	MF		33288	S3				35998
R34	360	MF		33287	S4				35998
R35					S5				
R42	22	CF		28710	S6		With R6		35345
R43	22	CF		28710	S7		Part of R7		
R44	990k	MF	½	31927	S13		Part of R3		
R45	22	CF		28710	S14		Part of R4		
R46	470k	CC	10 ¼W	4906	S51				A4/36232
R47	1M	MF		26346	S52				29057
R48	18	CF		28709	LAMPS				
R49	16k	MF		29361	L20	FX1242			26986
R50	15k8	MF		33291	L21	FX1242			26986
R51	5k23	MF		33290	L22	FX1242			26986
R52	1k72	MF		33289	L23	FX1242			26986
R53	787	MF		33288	L24	FX1242			26986
R54	360	MF		33287	L25	FX1242			26986
R55					DIODES				
R58	68k	CF		21816	D53	IN4003			23462
R59	150k	CF		21821	D54	IN4003			23462
R90	100k	CF	1W	19061	D90	AAZ15			1635
R91	470	CF		21797	D91	AAZ15			1635
R92	4k7	CF		21805	SOCKETS				
R93	3M01	MF		29478	SKV				1222
R94	1M	MF		26346	SKW				1222
R95	499k	MF		26342	SKX				1222
R96	301k	MF		29477	SKZ				24913
R97	100k	MF		29476	CAPACITORS				
R98	100k	MF		29476	C20	.1μF	PE	400V	29495
C25	.01μF	CE(2)		500V	24902				