

OBDR

Server / Controller Compatibility Matrix:



OBDR is supported with an HP Tape Drive attached to one of the following controllers:

- | | |
|--|------------|
| A. 64-Bit/133 MHz Single Channel Ultra320 SCSI G2 Adapter | 374654-B21 |
| B. 64-bit/133 MHz Dual Channel Ultra320 SCSI Adapter | 268351-B21 |
| C. Smart Array 641 and 642 Ultra320, PCI-X Adapters | |
| • 641: 291966-B21 | |
| • 642: 291967-B21 | |
| D. Smart Array 6402 and 6404 high performance Ultra320, PCI-X Adapters | |
| • 6402: 273915-B21 | |
| • 6404: 273914-B21 | |
| E. Integrated U320 controller | |
| F. Integrated Smart Array 6i controller | |

Notes:

1. U320 SCSI Adapters (A & B) require BIOS 5.05.18.02 to correct a known issue. The SCSI hard drive cannot be detected during the OBDR restore process when the server contains two U320 SCSI Adapters. Click [<here>](#) to download this latest BIOS
2. Smart Array 64x and 640x controllers (C & D) only support HP DAT40 and DAT72 hot plug tape drives
3. The integrated Smart Array 6i controller supports HP DAT40 and DAT72 hot plug tape drives and all external HP tape drives

OBDR

Server / Controller Compatibility Matrix:



ML Servers	Attach tape drive to this SCSI Controller
ML110 G3	A
ML150 G2	A
ML310 G3	A, B, C, D
ML350 G4	A, B, C, D, E
ML370 G4	A, B, C, D, E
ML570 G3	B, C, D, E

DL Servers	
DL140 G2	A, B
DL145 G2	A, B
DL320 G3	B, C, D
DL360 G4	A, B, C, D, F
DL380 G4	A, B, C, D, F
DL385	B, C, D, F
DL560	B, C, D
DL580 G3	B, C, D, F
DL585 G2	B, C, D,