



Voltage Chart*

Tube No.	Tube Type	Function	E _k	E _g	E ₅₀	E _p	E _b
V1a	12AX7	Chan I Pre amp	+1	0	—	+127	+272
V1b	12AX7	Chan II Pre amp	+1	0	—	+127	+272
V2a	12AX7	Chan I Amp	+2.1	0	—	+210	+280
V2b	12AX7	Chan II Amp	+2.1	0	—	+210	+280
V3a	12AX7	Chan I φ Splitter	+58	+25	—	+220	+280
V3b	12AX7	Chan II φ Splitter	+58	+25	—	+220	+280
V4	6BQ5	Chan I Output	-10.6	0	+312	+305	+312
V5	6BQ5	Chan II Output	+10.6	0	+312	+305	+312
V6	6BQ5	Chan I Output	+10.6	0	+312	+305	+312
V7	6BQ5	Chan II Output	+10.6	0	+312	+305	+312
V8	GZ34	Rect.	+320	—	—	310	310

* VOLTAGES TO CHASSIS WITH 20,000-Ω/V METER

Gibson STEREO
88-S