

Ersatzteilliste - Bill of Materials				
	173042	VENICE 240 120V		
	173044	VENICE 240 240V		
	173020	VENICE 240 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
		<b>Zubehör</b>		<b>Accessories &amp; packaging material</b>
	359941	BEDIENUNGSANL. VENICE	1	owner's manual VENICE
	346832	KABEL-NETZ UL/CSA 10A/125V	1	power cable US
	354619	KABEL-NETZ SAA 10A/250V	1	power cable UK
	300425	KABEL-NETZ 2.0 M 10A	1	power cable Europe
	302587	SICHER T 3.150 A/250V	1	fuse 3.15A slow blow
	302583	SICHER T 1.600 A/250V	1	fuse 1.6A slow blow / US only !!
	328391	SICHER-HALTER-KAPPE FEK	1	fuse holder carrier
	360003	SCHUTZBEZUG VENICE 240	1	dust cover VENICE 240
	360005	KRT. VENICE 240	1	carton inner V240
	360006	KRT. VENICE 240 AUSSEN	1	carton outer V240
	359944	STYROPOR-EINL. LI. VENICE	1	foam left hand
	359945	STYROPOR-EINL. RE. VENICE	1	foam right hand
	338158	SCHUTZHÜLLE 800X1200X0,07	1	plastic bag
		<b>Mechanische Teile</b>		<b>Cabinet material</b>
	341592	STECKER-FL. XLR 6POL	1	connector XLR male 6-pin
	359877	DK 11,4 GR/WS/DG B 6FL	49	knob rotary l.gr/wh/l.gr
	359876	DK 11,4 DG/WS/GR B 6FL	23	knob rotary gr/wh/l.gr
	359878	DK 11,4 DG/WS/BL B 6FL	40	knob rotary gr/wh/bl
	359879	DK 11,4 GR/WS/BL B 6FL	32	knob rotary l.gr/wh/bl
	359990	DK 11,4 DG/WS/DG B 6FL	20	knob rotary gr/wh/gr
	359991	DK 11,4 GR/WS/GN B 6FL	42	knob rotary l.gr/wh/gn
	358364	DK 11,4 GR/WS/RT B 6FL	46	knob rotary l.gr/wh/rd
	359993	DK 11,4 DG/SW/GE B 6FL	44	knob rotary gr/blk/yl
	359994	DK 11,4 GR/SW/GE B 6FL	1	knob rotary l.gr/blk/yl
	359995	DK 11,4 DG/WS/RT B 6FL	2	knob rotary gr/wh/rd
	359946	SK 24X11 GR/SW 4X1,2	20	knob slide l.gr/blk
	359947	SK 24X11 BL/SW 4X1,2	4	knob slide bl/blk
	359948	SK 24X11 RT/SW 4X1,2	3	knob slide rd/blk
	359949	SK 24X11 GN/SW 4X1,2	2	knob slide gn/blk
	359645	TK 9,8X9,8 RT 3,3	25	knob switch red square
	360000	TK 7,5X6 RT 3,3	22	knob switch red small
	359999	TK 9,8X6 RT 3,3	2	knob switch red mid
	358363	TK 7,5X6 GR 3,3	95	knob switch l.gr small
	358360	TK 9,8X6 GR 3,3	34	knob switch l.gr mid
	359863	TK 2,8 SW 3,3	20	knob switch blk +48V
	359648	EINLEGEBLENDE VENICE 240	1	logo VENICE 240
	335589	FUSS-GUMMI SJ 5009 SW	5	rubber foot
	358632	KABEL-KONFEKT-BUS 12POL 3X	1	ribbon cable 12-way 3conn
	358633	KABEL-KONFEKT-BUS 12POL 3X	1	ribbon cable 12-way 3conn
	358635	KABEL-KONFEKT-BUS 12POL 4X	1	ribbon cable 12-way 4conn
	358686	KABEL-KONFEKT 8POL 0.930M	1	ribbon cable assy 8-way
	358687	KABEL-KONFEKT 8POL 1.120M	2	ribbon cable assy 8-way

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
	358688	KABEL-KONFEKT 12POL 0.900M	1	ribbon cable assy 12-way
	358689	KABEL-KONFEKT 12POL 0.800M	1	ribbon cable assy 12-way
	358690	KABEL-KONFEKT 12POL 0.720M	1	ribbon cable assy 12-way
	354302	KABEL-KONFEKT 6POL 0.600M	1	ribbon cable 6-way
	348388	KABEL-KONFEKT 10POL 0.620M	2	ribbon cable assy 10-way
	341984	KABEL-KONFEKT 4POL 0.150M	1	ribbon cable assy 4-way
	353397	KABEL-KONFEKT 18POL 0.110M	10	ribbon cable assy 18-way
	358390	SEITENTEIL LINKS VENICE	1	side wing left hand
	358534	SEITENTEIL RECHTS VENICE	1	side wing rihgt hand
	359769	FRONTLEISTE VENICE 240	1	armrest VENICE 240
	359631	FRONTBL-BED VENICE 240	1	front panel VENICE 240
	359632	RÜCKWAND-BED VENICE 240	1	rear panel VENICE 240
	358691	RKT VENICE 100-240V	1	mains transformer VENICE
		<b>Printplatten, bestückt</b>		<b>Printed circuit board assemblies</b>
	<b>852778</b>	<b>PCBAR#VENICE 240/320</b>	<b>1</b>	<b>pcb assy 85277 power supply</b>
CNACx	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNGND	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNPE2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNPE3	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNT01	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNT02	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN00x	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN02A	344975	MESSERLST. 10POL	1	connector male 10-pin
CN021	344862	MESSERLST. 8POL	1	connector male 8-pin
CN022	345489	MESSERLST. 6POL	1	connector male 6-pin
C0001	341714	KO-SO 0.10MF 275V 20% K	1	safety cap 100nF/275V
C0002	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0003	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0004	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0005	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0008	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0009	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0010	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0011	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0012	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0013	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0014	327815	KO-EL 22.000MF 25V	1	cap electrolytic 22uF/25V
C0015	327815	KO-EL 22.000MF 25V	1	cap electrolytic 22uF/25V
C0016	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0017	341920	KO-EL 470.000MF 63V	1	cap electrolytic 470uF/63V
C0018	301478	KO-EL 22.000MF 63V	1	cap electrolytic 22uF/63V
C0019	301491	KO-EL 100.000MF 50V	1	cap electrolytic 100uF/50V
C0020	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0021	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0022	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0023	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0024	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0025	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0026	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0027	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0028	327815	KO-EL 22.000MF 25V	1	cap electrolytic 22uF/25V

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C0029	301491	KO-EL 100.000MF 50V	1	cap electrolytic 100uF/50V
C0030	341920	KO-EL 470.000MF 63V	1	cap electrolytic 470uF/63V
C0031	341920	KO-EL 470.000MF 63V	1	cap electrolytic 470uF/63V
C0032	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0033	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
D0005	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0006	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0007	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0008	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0009	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D001A	304364	DIODZ ZPY 30V 1.30W	1	diode zener 30V
D0010	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0011	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0012	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0013	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0014	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0015	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0016	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0017	358946	DIODE 1N 5401 BEARB.AUS	1	diode 1N 5401
D0018	358946	DIODE 1N 5401 BEARB.AUS	1	diode 1N 5401
D0019	358946	DIODE 1N 5401 BEARB.AUS	1	diode 1N 5401
D0020	358946	DIODE 1N 5401 BEARB.AUS	1	diode 1N 5401
D0021	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0025	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0026	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
E0001	356656	RELAIS 845-N-2C-S-24VDC	1	relay 24V
E0002	356656	RELAIS 845-N-2C-S-24VDC	1	relay 24V
E0003	356745	RELAIS M4-24H	1	relay 24V
F0002	302587	SICHER T 3.150 A/250V	1	fuse 3.15A slow blow
F0003	302587	SICHER T 3.150 A/250V	1	fuse 3.15A slow blow
F0004	302582	SICHER T 1.000 A/250V	1	fuse 1A slow blow
F0005	305205	SICHER T 2.500 A/250V	1	fuse 2.5A slow blow
G0001	357140	GLRI GBU 8K	1	rectifier
I0001	354199	IC SPNG.REGL. LM 317 T	1	IC LM 317 voltage regulator
I0002	354929	IC SPNG.REGL. LM 337 T	1	IC LM 337 voltage regulator
I0003	354199	IC SPNG.REGL. LM 317 T	1	IC LM 317 voltage regulator
I0004	354199	IC SPNG.REGL. LM 317 T	1	IC LM 317 voltage regulator
JS001	338835	STECKER-KALTGERÄTE	1	connector male mains
00010	301233	TRANS BD 246 B	0	transistor BD 246 B
00010	301234	TRANS BD 245 B	0	transistor BD 245 B
Q0003	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0004	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0005	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0006	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0007	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0008	348591	TRANS BC 618 DARL. TO 92	1	transistor BC 618
Q0009	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
S0001	354927	SCHALTER-NETZ	1	switch mains
00005	303576	SICHER-HALTE-FEDER	8	fuse clip
00010	328390	SICHER-HALTER FAU	1	fuse holder

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
	<b>813468</b>	<b>PCBAR#VENICE 160/240/320</b>	<b>2</b>	<b>pcb assy 81346 input mono</b>
CN006	348802	MESSERLST. 12POL	1	connector male 12-pin
CN007	348802	MESSERLST. 12POL	1	connector male 12-pin
CN008	348802	MESSERLST. 12POL	1	connector male 12-pin
CN01y	346759	MESSERLST. 18POL	1	connector male 18-pin
C001A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C0017	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C002A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C003A	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C004A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C006A	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C007A	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C008A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C009A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C010A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C011A	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C012A	300302	KO-FOL 1200.000PF 100V 5%	1	cap mylar 1200pF
C013A	326923	KO-FOL 3300.000PF 63V 5%	1	cap mylar 3300pF
C014A	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C015A	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C016A	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C017A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C018A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C020A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C021A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C022A	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C023A	358639	KO-EL 220.000MF 16V	1	cap electrolytic 220uF/16V
C024A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C025A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C028A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C029A	357451	KO-KER 68.0PF 100V 2%	1	cap ceramic 68pF
C030A	357451	KO-KER 68.0PF 100V 2%	1	cap ceramic 68pF
C031A	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C032A	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C080A	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C081A	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C090A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C091A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C82AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C83AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C84AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C85AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C86AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C87AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C88AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C89AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
D001A	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D005A	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D006A	354005	LED GE 3MM LOW CURRENT	1	led yellow
D007A	354003	LED RT 3MM LOW CURRENT	1	led red
D008A	354004	LED GN 3MM LOW CURRENT	1	led green

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
D009A	354003	LED RT 3MM LOW CURRENT	1	led red
D010A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D011A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D012A	354005	LED GE 3MM LOW CURRENT	1	led yellow
I001A	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I02AB	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I03AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I04AB	358661	IC NJM 2060 D	1	IC NJM 2060
I05AB	358661	IC NJM 2060 D	1	IC NJM 2060
I06AB	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I07AB	343502	IC LM 2901 N	1	IC LM 2901
Q001A	343536	TRANS 2SA 1084 E TO 92	1	transistor 2SA 1084 E
Q002A	343536	TRANS 2SA 1084 E TO 92	1	transistor 2SA 1084 E
Q003A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005A	348421	TRANS 2N 3906	1	transistor 2N 3906
R086A	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R087A	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S001A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003A	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S004A	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S005A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S006A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S007A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
VR01A	357442	P-DREH 2X 5KOHM LIN/LOG-	1	pot 2x5k Ohm
VR02A	357441	P-DREH 20KOHM LIN	1	pot 20k Ohm
VR03A	357435	P-DREH 2X200KOHM LOG-	1	pot 2x200k Ohm
VR04A	357439	P-DREH 10KOHM LIN	1	pot 10k Ohm
VR05A	357435	P-DREH 2X200KOHM LOG-	1	pot 2x200k Ohm
VR06A	357439	P-DREH 10KOHM LIN	1	pot 10k Ohm
VR07A	357441	P-DREH 20KOHM LIN	1	pot 20k Ohm
VR08A	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR09A	358685	P-DREH 2X 10KOHM LOG-/LOG+	1	pot 2x10k Ohm
VR10A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR11A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR12A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR13A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR14A	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR15A	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
	<b>822308</b>	<b>PCBAR#VENICE 160/240/320</b>	<b>1</b>	<b>pcb assy 82230 input stereo</b>
A0003	356641	KABEL-KONFEKT 6POL 0.230M	1	ribbon cable assy 6-way
CN007	348802	MESSERLST. 12POL	1	connector male 12-pin
CN008	348802	MESSERLST. 12POL	1	connector male 12-pin
CN01E	346759	MESSERLST. 18POL	1	connector male 18-pin
CN01F	346759	MESSERLST. 18POL	1	connector male 18-pin
CN017	344862	MESSERLST. 8POL	1	connector male 8-pin
CN018	344862	MESSERLST. 8POL	1	connector male 8-pin
CN020	348802	MESSERLST. 12POL	1	connector male 12-pin
CN021	344862	MESSERLST. 8POL	1	connector male 8-pin
CN022	345489	MESSERLST. 6POL	1	connector male 6-pin

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
CN024	348802	MESSERLST. 12POL	1	connector male 12-pin
CN025	348802	MESSERLST. 12POL	1	connector male 12-pin
CN026	344975	MESSERLST. 10POL	1	connector male 10-pin
CN06A	348802	MESSERLST. 12POL	1	connector male 12-pin
CN06B	348802	MESSERLST. 12POL	1	connector male 12-pin
CN19A	345489	MESSERLST. 6POL	1	connector male 6-pin
CN19B	345489	MESSERLST. 6POL	1	connector male 6-pin
C0001	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0002	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0003	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0004	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0005	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0006	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0007	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0008	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0009	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C001A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C0010	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0011	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0012	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0013	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0014	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0015	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0016	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0017	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0018	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0019	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C002A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C0020	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0021	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0022	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0023	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0024	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0025	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0026	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0027	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0028	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0029	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C003A	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C0030	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0033	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0034	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0035	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0036	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0037	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0038	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0039	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C004A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0040	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0041	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0042	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0043	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0044	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C0045	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0046	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0047	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0048	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0049	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C005A	358769	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0050	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0051	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0052	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0053	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0054	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0055	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0056	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0057	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0058	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0059	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C006A	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0060	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0061	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0062	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0063	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0064	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0065	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0066	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0067	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0068	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0069	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C007A	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0070	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0071	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0072	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0073	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0074	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0075	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0076	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0077	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0078	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0079	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C008A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0080	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0081	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0082	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0083	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0084	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0085	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0086	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0087	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0088	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0089	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C009A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0090	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0091	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0092	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C0093	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0094	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0095	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0096	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0097	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0098	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0099	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C01AB	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C010C	358769	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C010D	358769	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0100	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0101	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0102	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0103	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0104	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0105	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0106	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0107	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0108	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0109	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C011A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0110	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0111	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0112	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0113	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0114	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0115	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0116	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0117	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0118	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0119	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C012A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0120	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0121	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0122	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0123	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0124	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0125	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0126	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0127	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0128	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0129	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C013A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0130	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0131	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0132	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0133	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0134	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0135	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0136	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0137	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0138	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0139	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V



Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C014A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0140	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0141	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0142	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0143	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0144	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0145	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0146	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0147	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0148	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0149	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C015A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C015B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C015C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C015D	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0150	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0151	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0152	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0153	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0154	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0155	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0156	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0157	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0158	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0159	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C016A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0160	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0161	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0162	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0163	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0164	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0165	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0166	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0167	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0168	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0169	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C017A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0170	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0171	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0172	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0173	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0174	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0175	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0176	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0177	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0178	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0179	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0180	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0181	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0182	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0183	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0184	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C0185	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0186	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0187	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0188	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0189	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C019A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0190	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0191	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0192	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0193	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0194	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0195	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0196	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0197	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0198	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0199	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C02AB	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C02CD	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C020A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0200	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0201	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0202	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0203	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0204	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0205	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0206	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0207	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0208	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0209	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C021A	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C0210	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0211	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0212	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0213	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0214	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0215	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0216	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0217	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C022A	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C023A	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C024A	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C025A	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C026A	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C027A	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C028A	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C029A	357457	KO-FOL 1000.000PF 100V 5%	1	cap mylar 1nF
C03AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C03CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C030A	357457	KO-FOL 1000.000PF 100V 5%	1	cap mylar 1nF
C031A	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
C032A	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
C035A	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF
C036A	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C037A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C038A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C039A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C04AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C04CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C040A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C041A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C042A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C043A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C044A	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C045A	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C046A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C047A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C048A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C049A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C05AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C05CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C050A	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C051A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C052A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C053A	357451	KO-KER 68.0PF 100V 2%	1	cap ceramic 68pF
C054A	357451	KO-KER 68.0PF 100V 2%	1	cap ceramic 68pF
C055A	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C056A	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C057A	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C058A	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C059A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C06AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C06CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C07AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C07CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C08AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C08CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C081E	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C09AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C09CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C10AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C10CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C11AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C11CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C12AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C12CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C13AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C13CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C14AB	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C14CD	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0003	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0004	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0005	354004	LED GN 3MM LOW CURRENT	1	led green
D0006	354004	LED GN 3MM LOW CURRENT	1	led green
D0007	354004	LED GN 3MM LOW CURRENT	1	led green

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
D0008	354004	LED GN 3MM LOW CURRENT	1	led green
D0009	354004	LED GN 3MM LOW CURRENT	1	led green
D001A	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0010	354004	LED GN 3MM LOW CURRENT	1	led green
D0011	354004	LED GN 3MM LOW CURRENT	1	led green
D0012	354004	LED GN 3MM LOW CURRENT	1	led green
D0013	354004	LED GN 3MM LOW CURRENT	1	led green
D0014	354004	LED GN 3MM LOW CURRENT	1	led green
D0015	354004	LED GN 3MM LOW CURRENT	1	led green
D0016	354004	LED GN 3MM LOW CURRENT	1	led green
D0017	354004	LED GN 3MM LOW CURRENT	1	led green
D0018	354004	LED GN 3MM LOW CURRENT	1	led green
D0019	354004	LED GN 3MM LOW CURRENT	1	led green
D0020	354004	LED GN 3MM LOW CURRENT	1	led green
D0021	354004	LED GN 3MM LOW CURRENT	1	led green
D0022	354004	LED GN 3MM LOW CURRENT	1	led green
D0023	354004	LED GN 3MM LOW CURRENT	1	led green
D0024	354004	LED GN 3MM LOW CURRENT	1	led green
D0025	354004	LED GN 3MM LOW CURRENT	1	led green
D0026	354004	LED GN 3MM LOW CURRENT	1	led green
D0027	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0028	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0029	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0030	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0031	354003	LED RT 3MM LOW CURRENT	1	led red
D0032	354003	LED RT 3MM LOW CURRENT	1	led red
D0033	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0034	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0035	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0036	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0037	354004	LED GN 3MM LOW CURRENT	1	led green
D0038	354004	LED GN 3MM LOW CURRENT	1	led green
D0039	354004	LED GN 3MM LOW CURRENT	1	led green
D0040	354004	LED GN 3MM LOW CURRENT	1	led green
D0041	354004	LED GN 3MM LOW CURRENT	1	led green
D0042	354004	LED GN 3MM LOW CURRENT	1	led green
D0043	354004	LED GN 3MM LOW CURRENT	1	led green
D0044	354004	LED GN 3MM LOW CURRENT	1	led green
D0045	354004	LED GN 3MM LOW CURRENT	1	led green
D0046	354004	LED GN 3MM LOW CURRENT	1	led green
D0047	354004	LED GN 3MM LOW CURRENT	1	led green
D0048	354004	LED GN 3MM LOW CURRENT	1	led green
D0049	354004	LED GN 3MM LOW CURRENT	1	led green
D005A	354004	LED GN 3MM LOW CURRENT	1	led green
D0050	354004	LED GN 3MM LOW CURRENT	1	led green
D0051	354004	LED GN 3MM LOW CURRENT	1	led green
D0052	354004	LED GN 3MM LOW CURRENT	1	led green
D0053	354004	LED GN 3MM LOW CURRENT	1	led green
D0054	354004	LED GN 3MM LOW CURRENT	1	led green
D0055	354004	LED GN 3MM LOW CURRENT	1	led green
D0056	354004	LED GN 3MM LOW CURRENT	1	led green
D0057	354004	LED GN 3MM LOW CURRENT	1	led green
D0058	354004	LED GN 3MM LOW CURRENT	1	led green

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
D0059	354005	LED GE 3MM LOW CURRENT	1	led yellow
D006A	354003	LED RT 3MM LOW CURRENT	1	led red
D0060	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0061	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0062	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0063	354003	LED RT 3MM LOW CURRENT	1	led red
D0064	354003	LED RT 3MM LOW CURRENT	1	led red
D0065	354004	LED GN 3MM LOW CURRENT	1	led green
D0066	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0067	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0068	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0069	354005	LED GE 3MM LOW CURRENT	1	led yellow
D007A	354003	LED RT 3MM LOW CURRENT	1	led red
D0070	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0071	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0072	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0073	354003	LED RT 3MM LOW CURRENT	1	led red
D0074	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0075	354003	LED RT 3MM LOW CURRENT	1	led red
D0076	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0077	354004	LED GN 3MM LOW CURRENT	1	led green
D0078	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0079	354003	LED RT 3MM LOW CURRENT	1	led red
D008A	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0080	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0081	354004	LED GN 3MM LOW CURRENT	1	led green
D0082	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0083	354003	LED RT 3MM LOW CURRENT	1	led red
D0084	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0085	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0086	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0087	354003	LED RT 3MM LOW CURRENT	1	led red
D0088	354003	LED RT 3MM LOW CURRENT	1	led red
D0089	354004	LED GN 3MM LOW CURRENT	1	led green
D009A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0090	354004	LED GN 3MM LOW CURRENT	1	led green
D0091	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0092	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0093	354003	LED RT 3MM LOW CURRENT	1	led red
D0094	354003	LED RT 3MM LOW CURRENT	1	led red
D0095	354004	LED GN 3MM LOW CURRENT	1	led green
D0096	354004	LED GN 3MM LOW CURRENT	1	led green
D0097	354003	LED RT 3MM LOW CURRENT	1	led red
D0098	354005	LED GE 3MM LOW CURRENT	1	led yellow
D0099	354003	LED RT 3MM LOW CURRENT	1	led red
D010A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0100	354005	LED GE 3MM LOW CURRENT	1	led yellow
D011A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D012A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D013A	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0501	354003	LED RT 3MM LOW CURRENT	1	led red
E0001	357448	RELAIS	1	relay
E0002	357448	RELAIS	1	relay

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
H0001	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0003	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0004	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0005	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0006	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0007	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0008	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0002	343502	IC LM 2901 N	1	IC LM 2901
I0003	343502	IC LM 2901 N	1	IC LM 2901
I0004	343502	IC LM 2901 N	1	IC LM 2901
I0005	343502	IC LM 2901 N	1	IC LM 2901
I0006	343502	IC LM 2901 N	1	IC LM 2901
I0007	343502	IC LM 2901 N	1	IC LM 2901
I0008	343502	IC LM 2901 N	1	IC LM 2901
I0009	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I001A	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I0010	343502	IC LM 2901 N	1	IC LM 2901
I0011	343502	IC LM 2901 N	1	IC LM 2901
I0012	343502	IC LM 2901 N	1	IC LM 2901
I0013	343502	IC LM 2901 N	1	IC LM 2901
I0014	343502	IC LM 2901 N	1	IC LM 2901
I0015	343502	IC LM 2901 N	1	IC LM 2901
I0016	343502	IC LM 2901 N	1	IC LM 2901
I0017	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0018	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0019	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0020	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0021	344864	IC NJM 4556 AD 2-FACH OP	1	IC NJM 4556 D
I0022	344864	IC NJM 4556 AD 2-FACH OP	1	IC NJM 4556 D
I0023	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I0024	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0025	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0026	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0027	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0028	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0029	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0030	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0031	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0032	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0033	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0034	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0035	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0036	343502	IC LM 2901 N	1	IC LM 2901
I0037	343502	IC LM 2901 N	1	IC LM 2901
I0038	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0039	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0040	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0041	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0042	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0043	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0044	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
I0045	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0046	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0047	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0048	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0049	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0050	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0051	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0052	354934	IC NJM 2068 L SINGLE IN	1	IC NJM 2068 L
I0055	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I013A	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I02AB	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I02CD	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I03AB	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I03CD	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I04AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I04CD	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I05AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I05CD	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I06AB	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I06CD	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I07AB	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I07CD	354933	IC NJM 2068 D DUAL IN	1	IC NJM 2068
I08AB	358661	IC NJM 2060 D	1	IC NJM 2060
I08CD	358661	IC NJM 2060 D	1	IC NJM 2060
I09AB	358661	IC NJM 2060 D	1	IC NJM 2060
I09CD	358661	IC NJM 2060 D	1	IC NJM 2060
I10AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I10CD	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I11AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I11CD	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I12AB	343502	IC LM 2901 N	1	IC LM 2901
I12CD	343502	IC LM 2901 N	1	IC LM 2901
I17AB	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I17CD	358898	IC MC 33178 2FACH OP	1	IC MC 33178
JS001	354000	BUCHSE-FL. XLR 3POL SW	1	connector XLR female 3-pole
JS002	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS003	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS004	357432	BUCHSE-FL. XLR 4POL PRINTB	1	connector XLR male 4-pole
JS005	357432	BUCHSE-FL. XLR 4POL PRINTB	1	connector XLR male 4-pole
Q0001	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0002	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0003	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0004	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0005	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0006	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q001A	343536	TRANS 2SA 1084 E TO 92	1	transistor 2SA 1084 E
Q002A	343536	TRANS 2SA 1084 E TO 92	1	transistor 2SA 1084 E
Q003A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005A	348421	TRANS 2N 3906	1	transistor 2N 3906
R01AB	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R01CD	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0141	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
R0142	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R02AB	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R02CD	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0209	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0210	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S0001	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0007	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0008	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0009	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S001A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0010	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0011	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0012	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0013	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0014	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0015	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0016	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0017	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0018	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0019	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S002A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0020	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0021	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0022	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0023	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0024	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0025	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0026	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0027	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0028	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0029	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003A	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0030	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0031	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0032	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0033	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0034	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0035	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0036	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0037	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0038	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0039	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004A	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0041	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0042	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0043	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0044	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S005A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S006A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S007A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
VR01A	357442	P-DREH 2X 5KOHM LIN/LOG-	1	pot 2x5k Ohm
VR015	357444	P-SHIB 2X 50KOHM LOG+	1	fader 2x50k Ohm
VR016	357434	P-DREH 2X 50KOHM LOG+	1	pot 2x50k Ohm



Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
VR017	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k Ohm
VR018	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR019	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR02A	357433	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR020	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR021	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR022	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR023	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k Ohm
VR024	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR025	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k Ohm
VR026	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR027	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k Ohm
VR028	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR029	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k Ohm
VR03A	357440	P-DREH 2X 50KOHM LIN	1	pot 2x50k Ohm
VR030	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR031	357443	P-SHIB 10KOHM LOG+	1	fader 10k Ohm
VR032	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR033	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR034	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR035	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR036	357433	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR037	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR038	357433	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR039	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR04A	357438	P-DREH 2X 20KOHM LIN	1	pot 2x20k OHm
VR040	357444	P-SHIB 2X 50KOHM LOG+	1	fader 2x50k Ohm
VR041	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR042	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR043	357444	P-SHIB 2X 50KOHM LOG+	1	fader 2x50k Ohm
VR044	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR045	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR047	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR05A	357438	P-DREH 2X 20KOHM LIN	1	pot 2x20k OHm
VR06A	357440	P-DREH 2X 50KOHM LIN	1	pot 2x50k Ohm
VR07A	357444	P-SHIB 2X 50KOHM LOG+	1	fader 2x50k Ohm
VR08A	358685	P-DREH 2X 10KOHM LOG-/LOG+	1	pot 2x10k Ohm
VR09A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR10A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR11A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR12A	357437	P-DREH 50KOHM LOG-	1	pot 50k Ohm
VR13A	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
VR14A	357436	P-DREH 2X 50KOHM LOG-	1	pot 2x50k Ohm
	<b>862698</b>	<b>PCBAR#VENICE 160/240/320</b>	<b>1</b>	<b>pcb assy 86269 connectors</b>
CN00L	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN002	344975	MESSERLST. 10POL	1	connector male 10-pin
CN009	341937	MESSERLST. 4POL	1	connector male 4-pin
CN01A	346759	MESSERLST. 18POL	1	connector male 18-pin
CN017	344862	MESSERLST. 8POL	1	connector male 8-pin
CN018	344862	MESSERLST. 8POL	1	connector male 8-pin
CN020	348802	MESSERLST. 12POL	1	connector male 12-pin

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
CN024	348802	MESSERLST. 12POL	1	connector male 12-pin
CN025	348802	MESSERLST. 12POL	1	connector male 12-pin
CN026	344975	MESSERLST. 10POL	1	connector male 10-pin
CN09A	341937	MESSERLST. 4POL	1	connector male 4-pin
CN100	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN120	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN230	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN240	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
C0001	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0002	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0003	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0004	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0005	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0006	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0007	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0008	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0009	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0011	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0010	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0011	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0012	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0013	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0014	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0015	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0016	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0017	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0018	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0019	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0021	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0020	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0021	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0022	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0023	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0024	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0025	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0026	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0027	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0028	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0031	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0030	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0031	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0032	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0033	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0034	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0035	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0036	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0037	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0038	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0039	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C004A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C004I	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0040	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C0041	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0042	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0044	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0045	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0046	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0047	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0048	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0049	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C005A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005I	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0050	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0051	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0052	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0053	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0054	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0055	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0056	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0057	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0058	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0059	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C006A	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0060	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0061	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0062	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0063	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0064	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0069	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C007A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0070	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0071	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0072	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0073	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0074	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0075	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0076	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0077	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C008A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0080	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0081	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0082	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0085	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0086	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0089	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C009A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C009I	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0090	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0093	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0094	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0095	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0096	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0097	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0098	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0099	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C010A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C010I	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0100	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0101	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0102	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0103	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0104	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0105	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0106	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0107	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0108	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0109	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0110	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0111	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0112	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0113	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0114	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0115	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0116	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0117	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0118	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0119	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C012A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0120	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C013A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C014A	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D001A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D002A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D003A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D004A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D005A	357450	LED GE 3MM LY 3369-EH	1	led yellow
E0001	357448	RELAIS	1	relay
E0002	357448	RELAIS	1	relay
E0003	357448	RELAIS	1	relay
E0004	357448	RELAIS	1	relay
E0005	357448	RELAIS	1	relay
E0006	357448	RELAIS	1	relay
E0007	357448	RELAIS	1	relay
E0008	357448	RELAIS	1	relay
FT01A	357449	KO-SO 1000PF 100V FILTER	1	rf capacitor 1nF/100V
FT02A	357449	KO-SO 1000PF 100V FILTER	1	rf capacitor 1nF/100V
I0001	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0002	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0003	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0004	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0005	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0006	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0007	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0008	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
JS001	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS002	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
JS003	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS004	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS005	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS006	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS007	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS008	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS009	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS01A	354000	BUCHSE-FL. XLR 3POL SW	1	connector XLR female 3-pole
JS010	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS011	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS012	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS013	354002	BUCHSE-CINCH 4X CINCH	1	connector cinch
JS014	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS015	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS016	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS017	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS018	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS019	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS02A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS020	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS021	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS022	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS023	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS024	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS025	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS026	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS027	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS028	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS029	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS03A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS030	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS031	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS04A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
S0001	340434	SCHALTER-SCHIEBE 2XUM	1	switch slide dpdt
S0002	340434	SCHALTER-SCHIEBE 2XUM	1	switch slide dpdt
S001A	354006	SCHALTER-RAST 2XUM	1	switch dpdt
VR001	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR002	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR003	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR004	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR005	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR006	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR007	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
VR008	356753	WI-TRI 5.00 KOHM LIN	1	trim pot 5k Ohm
	<b>862708</b>	<b>PCBAR#VENICE 240/320</b>	<b>1</b>	<b>pcb assy 86270 conn. ext.</b>
CN001	346759	MESSERLST. 18POL	1	connector male 18-pin
CN002	346759	MESSERLST. 18POL	1	connector male 18-pin
CN003	346759	MESSERLST. 18POL	1	connector male 18-pin
CN004	346759	MESSERLST. 18POL	1	connector male 18-pin
CN009	341937	MESSERLST. 4POL	1	connector male 4-pin
C003A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
C004A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C006A	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C007A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C008A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C009A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C010A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C012A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C013A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C014A	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
D001A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D002A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D003A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D004A	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D005A	357450	LED GE 3MM LY 3369-EH	1	led yellow
FT01A	357449	KO-SO 1000PF 100V FILTER	1	rf capacitor 1nF/100V
FT02A	357449	KO-SO 1000PF 100V FILTER	1	rf capacitor 1nF/100V
JS01A	354000	BUCHSE-FL. XLR 3POL SW	1	connector XLR female 3-pole
JS02A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS03A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS04A	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
Q0003	348423	TRANS MPSA 92	1	transistor MPSA 92
S001A	354006	SCHALTER-RAST 2XUM	1	switch dpdt