

Technical Bulletin



November 28, 1966

TO ALL MAINTENANCE ENGINEERS - CHANGES

NO. MODELS

SUBJECT: SERVICE MANUAL AND COMMERCIAL EQUIVALENT
FOR TRANSISTORS AND DIODES

43 Series 10
Tone Cabinet

Enclosed is a copy of the Service Manual for the recently introduced Series 10 Tone Cabinets. We suggest you review this manual thoroughly in order to acquaint yourself with this new all solid state system.

Listed below you will find the commercial equivalent numbers for all of the transistors and diodes in the Series 10 Tone Cabinet. We suggest you keep this list with the service manual for future reference.

The commercial numbers listed should, in most cases, be available from your local electronics supplier.

Transistor and Diode Commercial Replacement Recommendation

<u>HAMMOND P/N</u>	<u>CIRCUIT DESIGNATION</u>	<u>COMMERCIAL P/N</u>
01-1205-0	Q-305, Q-406, Q-407, Q-506, Q-507	Delco 2N392
01-1205-1	Q-306, Q-307	Delco or Texas Instrument 2N458B
01-1206	Q-304	GE16A787
01-2104	Q-302, Q-403, Q-404, Q-503, Q-504	2N3393
01-2107	Q-301, Q-401, Q-402, Q-501, Q-502	2N3391A
01-2108	Q-303	2N3391
01-2111-0	Q-405, Q-505	2N697
01-2406	ALL DIODES	Motorola MR1031

NOTE: This bulletin is a confidential letter to the Hammond dealer organization and is not for general distribution.
HAMMOND ORGAN COMPANY, 4200 W. DIVERSEY AVE., CHICAGO, ILL., 60639